

## KettyBot - Quick Start Guide

Power on: long-press the power button for 3s.



delivery mode interface and click start.



**Customer attraction:** Select the customer attraction mode attraction to solicit customers by itself.



Dish-Return: In the dish-return mode, select the table number and click start, and we can set the dwell time and return interval in the settings

<	Please select a g	roup	
	🗖 Area A 📀 💿	01 02 03	•
	🗆 Area B		0
	Go back to inventory	Start	
			_

Charging: connect to the charger immediately when the power is lower than 20%. Or replace the quick-release battery (if any).



**Delivery:** Click on the corresponding table number on the **Cruise:** Select the cruise route on the cruise mode interface and click start.



Escorting: Select the table number in the escorting mode and click to go, the robot will go to the location for customer interface, and the customer can follow the robot to the table.

Cala	ct a table					÷ 1	D 33%
	umber.	<	All			>	
		01					٥
	1						
L L	)1						
	_						
_	_						
	escorting on	S	tart I	Escor	ting		

Self-charging: Click "charging", the robot automatically returns to the charging pile for charging (requires a charging pile)



## Note

- Press the emergency button on the top of the robot to make it stop immediately. Then it cannot run and the button 1. needs to be rotated to make it move;
- Forbid to transport liquid dishes, such as soup, hotpot, etc.; it is easy to cause liquid spillage and other accidents; 2.
- The robot has an automatic obstacle avoidance function, but it is strictly forbidden to block the robot suddenly during 3. its running. Otherwise, it may cause an accident;
- The lidar, RGBD and Marker camera are strictly prohibited from being blocked by any objects; 4.
- 5. Please designate a person to charge the robot, **don't** charge it **unattended**;
- Please keep the robot and its charging port in a dry storage location and at room temperature. Forbidden to place the 6. robot and charger in a high-temperature area for charging (>40°C) and let water in;